

DULUX L 55 W/930 2G11

Kod produktu: 56018



Dane techniczne:

- Construction wattage [PICOS] 55.00 W
- Nominal wattage 55.00 W
- Color temperature 3000 K
- Nominal luminous flux 4000 Im
- Rated luminous flux 4000 Im
- Light color as per EN 12464-1 LUMILUX DE LUXE Warm White
- Overall length 533.0 mm
- Length 533.0 mm
- Nominal lamp life time 20000 h
- Rated lamp life time 20000 h
- Energy efficiency class A
- Lamp mercury content 1.7 mg
- Energy consumption 61 kWh/1000h
- ILCOS FSDH-55/930-/P/-2G11-43,9/533
- Product weight 115.00 g
- Product remark For ECG operation only
- Light color 930
- Luminous flux at 25 °C 4000 Im
- Rated LLMF at 4,000 h 0.85
- Rated LLMF at 6,000 h 0.83
- Rated LLMF at 8,000 h 0.81
- Rated LLMF at 12,000 h 0.79
- Length with base excl. base pins/connection ${\bf 533.00}\ mm$
- Rated LLMF at 16,000 h 0.78
- Rated LLMF at 20,000 h 0.76
- Color rendering index Ra ≥90
- Tube diameter 17.5 mm
- Lifespan 20000 h
- Rated lamp survival factor at 2,000 h 0.99
- Rated lamp survival factor at 4,000 h 0.99
- Rated lamp survival factor at 6,000 h 0.99
- Operation mode LLMF/LSF HF
- Rated lamp survival factor at 8,000 h 0.99
- Rated lamp survival factor at 12,000 h 0.95
- Rated lamp survival factor at 16,000 h 0.81



- Rated lamp survival factor at 20,000 h 0.50
- Base (standard designation) 2G11
- Appropriate disposal acc. to WEEE Yes
- Suitable for indoor **Yes**
- Rated ambient temp.w.max.luminous flux 25.0 °C

Product benefits

- Very economical and efficient
- Good quality of light
- Outstanding luminous efficiency
- Long service life
- Improved maintenance

Areas of application

- Offices, public buildings
- Shops
- · Supermarkets and department stores
- Hotels, restaurants
- Industry

Product features

- Short and compact pin-base lamp with double-turn tubes
- Single-ended four-pin plug-in 2G11 base
- Color rendering index Ra: []90
- Average life: 20,000 h (with QUICKTRONIC)

Equipment / Accessories

• Suitable for operation on electronic and conventional control gear

Safety advice

In case of lamp breakage: www.osram.com/brokenlamp





