

MHN-TD 250W/842 FC2 1CT/12

Kod produktu: 58105



Dane techniczne:

- Cap-Base **FC2**
- Bulb **T27 [T 27mm]**
- Color Code **842 [CCT of 4200K]**
- Color Designation (text) **Cool White**
- Color Temperature **4200 K**
- Dimmable **No**
- Energy Efficiency Label (EEL) **A+**
- Energy consumption kWh/1000h **277 kWh**
- Diameter D **27.5 (max) mm**
- Overall Length C **161.6 (max) mm**
- Full product code **928078605121**
- Full product name **MHN-TD 250W/842 FC2 1CT**
- Order code **928078605121**
- Order product name **MHN-TD 250W/842 FC2 1CT/12**
- Packing configuration **12**
- Pieces per pack **1**
- Bar code on outerbox - EAN3 **8711500183712**
- Bar code on pack - EAN1 **8711500734006**
- Packs per outerbox **12**
- Logistic code(s) - 12NC **928078605121**
- Net weight per piece **0.054 kg**
- Bulb Finish **Clear**
- Cap-Base Information **na**
- Lamp Wattage **250 W**
- Operating Position **p45 [Parallel +/-45D or Horizontal(HOR)]**
- Color Rendering Index **85 Ra8**
- ILCOS code **MD-250/42/1B-H-FC2-/H**
- Bulb Temperature **650 (max) C**
- Pinch Temperature **280 (max) C**
- Life to 50% failures **9000 hr**
- Light Center Length L **69.5 mm**
- Mercury (Hg) Content **16 mg**
- Insertion Length B **135.4 (max) mm**
- Lumen Maintenance 2000h **75 %**
- Chromaticity Coordinate X **370 -**
- Chromaticity Coordinate Y **370 -**
- Lumen Maintenance 5000h **70 %**
- Lamp Wattage EM 25°C, Nominal **250.0 W**

- Lamp Wattage EM 25°C, Rated **252.0 W**
- Luminous Efficacy Lamp EM **80 Lm/W**
- Luminous Flux Lamp EM **20000 Lm**
- Lamp Voltage **100 V**
- Lamp Current EM **3 A**
- Lumen Maintenance 10000h **60 %**
- Luminance Average EM **1000 cd/cm²**
- Life to 20% failures **7000 hr**
- Life to 5% failures **5000 hr**
- Arc Length O **27 mm**
- Diameter D [inch] **1.08 in**
- Light Center Length L [inch] **2.74 in**
- Overall Length C [inch] **6.36 (max) in**
- Footnotes HID **374 [Performance may not be satisfactory unless operated within specified operating positions. (374)]**

Double-ended quartz Metal-halide lamp



